

Sensitivity Analysis

We consider:

Sensitivity Analysis

We consider:

- Changes to a cost for a NBV.

Sensitivity Analysis

We consider:

- Changes to a cost for a NBV.
- Changes to a cost for a BV.

Sensitivity Analysis

We consider:

- Changes to a cost for a NBV.
- Changes to a cost for a BV.
- Change to a supply/demand pair.

Change to a cost for a NBV

- If c_{ij} changes to $c_{ij} + \Delta$, then u_i, v_j

Change to a cost for a NBV

- If c_{ij} changes to $c_{ij} + \Delta$, then u_i, v_j will not change (we used BVs for those).

Change to a cost for a NBV

- If c_{ij} changes to $c_{ij} + \Delta$, then u_i, v_j will not change (we used BVs for those).
- Only change is to “Row 0” in cell (i, j) :

Change to a cost for a NBV

- If c_{ij} changes to $c_{ij} + \Delta$, then u_i, v_j will not change (we used BVs for those).
- Only change is to “Row 0” in cell (i, j) :

$$(c_{ij} + \Delta) - (u_i + v_j) =$$

Change to a cost for a NBV

- If c_{ij} changes to $c_{ij} + \Delta$, then u_i, v_j will not change (we used BVs for those).
- Only change is to “Row 0” in cell (i, j) :

$$(c_{ij} + \Delta) - (u_i + v_j) = (c_{ij} - (u_i + v_j)) + \Delta$$

Example 1

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	35
			10		25				
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		20		30		30		125

Example 1

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		$8 + \Delta$	10	6	25	10		9	35
$u_2 = 3$	45	9		12	5	13		7	50
$u_3 = 3$		14	10	9		16	30	5	40
Demand	45		20		30		30		125

Example 1

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		$8 + \Delta$		6		10		9	35
	$(2 + \Delta)$		10		25				
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		20		30		30		125

Example 1

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	$8 + \Delta$ $(2 + \Delta)$	6 10	10 25	9	35
$u_2 = 3$	9 45	12	13 5	7	50
$u_3 = 3$	14	9 10	16	5 30	40
Demand	45	20	30	30	125

Current basis is optimal as long as $\Delta > -2$.

Example 2

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	35
			10		25				
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		$16 + \Delta$		5	40
			10				30		
Demand	45		20		30		30		125

Example 2

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	35
			10		25				
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		$16 + \Delta$		5	40
			10		$(3 + \Delta)$		30		
Demand	45		20		30		30		125

Example 2

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	35
			10		25				
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		$16 + \Delta$		5	40
			10		$(3 + \Delta)$		30		
Demand	45		20		30		30		125

Current basis is optimal for $\Delta > -3$.

Changing a basic variable could change many of the u_i, v_j . We will have to re-compute them, and all of the other “Row 0” changes...

Example 3: Change cost for a BV

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		$10 + \Delta$		9	35
			10		25				
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		20		30		30		125

Example 2

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	$10 + \Delta$	9	35
$u_2 = 3$	9	12	13	7	50
$u_3 = 3$	14	9	16	5	40
Demand	45	20	30	30	125

Example 2

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	$10 + \Delta$	9	35
$u_2 = 3 - \Delta$	45	12	5	7	50
$u_3 = 3$	14	9	16	5	40
Demand	45	20	30	30	125

Example 2

	$v_1 = 6 + \Delta$		$v_2 = 6$		$v_3 = 10 + \Delta$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		$10 + \Delta$		9	35
			10		25				
$u_2 = 3 - \Delta$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		20		30		30		125

Example 2

	$v_1 = 6 + \Delta$		$v_2 = 6$		$v_3 = 10 + \Delta$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		$10 + \Delta$		9	35
			10		25				
$u_2 = 3 - \Delta$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		20		30		30		125

Now we compute the other “Row 0” values...

Example 2

	$v_1 = 6 + \Delta$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8 $(2 - \Delta)$	6 10	$10 + \Delta$ 25	9 (7)	35
$u_2 = 3 - \Delta$	9 45	12	13 5	7	50
$u_3 = 3$	14	9 10	16	5 30	40
Demand	45	20	30	30	125

Example 2

	$v_1 = 6 + \Delta$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8 $(2 - \Delta)$	6 10	$10 + \Delta$ 25	9 (7)	35
$u_2 = 3 - \Delta$	9 45	12 $(3 + \Delta)$	13 5	7	50
$u_3 = 3$	14	9 10	16	5 30	40
Demand	45	20	30	30	125

Example 2

	$v_1 = 6 + \Delta$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8 $(2 - \Delta)$	6 10	$10 + \Delta$ 25	9 (7)	35
$u_2 = 3 - \Delta$	9 45	12 $(3 + \Delta)$	13 5	7 $(2 + \Delta)$	50
$u_3 = 3$	14	9 10	16	5 30	40
Demand	45	20	30	30	125

Example 2

	$v_1 = 6 + \Delta$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8 $(2 - \Delta)$	6 10	$10 + \Delta$ 25	9 (7)	35
$u_2 = 3 - \Delta$	9 45	12 $(3 + \Delta)$	13 5	7 $(2 + \Delta)$	50
$u_3 = 3$	14 $(5 - \Delta)$	9 10	16 30	5 30	40
Demand	45	20	30	30	125

Example 2

	$v_1 = 6 + \Delta$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8 $(2 - \Delta)$	6 10	$10 + \Delta$ 25	9 (7)	35
$u_2 = 3 - \Delta$	9 45	12 $(3 + \Delta)$	13 5	7 $(2 + \Delta)$	50
$u_3 = 3$	14 $(5 - \Delta)$	9 10	16 $(3 - \Delta)$	5 30	40
Demand	45	20	30	30	125

Example 2

	$v_1 = 6 + \Delta$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8 $(2 - \Delta)$	6 10	$10 + \Delta$ 25	9 (7)	35
$u_2 = 3 - \Delta$	9 45	12 $(3 + \Delta)$	13 5	7 $(2 + \Delta)$	50
$u_3 = 3$	14 $(5 - \Delta)$	9 10	16 $(3 - \Delta)$	5 30	40
Demand	45	20	30	30	125

Five inequalities must remain satisfied in order for the current basis to remain optimal:

$$2 - \Delta > 0, \quad 3 + \Delta > 0, \quad 2 + \Delta > 0, \quad 5 - \Delta > 0, \quad 3 - \Delta > 0$$

Example 2

	$v_1 = 6 + \Delta$	$v_2 = 6$	$v_3 = 10 + \Delta$	$v_4 = 2$	Supply
$u_1 = 0$	8 $(2 - \Delta)$	6 10	$10 + \Delta$ 25	9 (7)	35
$u_2 = 3 - \Delta$	9 45	12 $(3 + \Delta)$	13 5	7 $(2 + \Delta)$	50
$u_3 = 3$	14 $(5 - \Delta)$	9 10	16 $(3 - \Delta)$	5 30	40
Demand	45	20	30	30	125

Five inequalities must remain satisfied in order for the current basis to remain optimal:

$$2 - \Delta > 0, \quad 3 + \Delta > 0, \quad 2 + \Delta > 0, \quad 5 - \Delta > 0, \quad 3 - \Delta > 0$$

so that

$$-2 < \Delta < 2$$

Change to s_i, d_j

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	$35 + \Delta$
$u_2 = 3$	45	12	5	7	50
$u_3 = 3$	14	9	16	5	40
Demand	45	20	30	30	125

Change to s_i, d_j

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	$35 + \Delta$
$u_2 = 3$	45	12	5	7	50
$u_3 = 3$	14	9	16	5	40
Demand	45	20	30	30	125

To stay balanced, a demand must also increase by Δ .
 Suppose we choose the second demand (so that cell (1,2) is basic)

Change to s_i, d_j , Cell (i, j) is Basic

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	$35 + \Delta$
			10		25				
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		$20 + \Delta$		30		30		125

Change to s_i, d_j , Cell (i, j) is Basic

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	
		$10 + \Delta$	25		$35 + \Delta$
$u_2 = 3$	9	12	13	7	
	45		5		50
$u_3 = 3$	14	9	16	5	
		10		30	40
Demand	45	$20 + \Delta$	30	30	125

Change to s_i, d_j , Cell (i, j) is Basic

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	
		$10 + \Delta$	25		$35 + \Delta$
$u_2 = 3$	9	12	13	7	
	45		5		50
$u_3 = 3$	14	9	16	5	
		10		30	40
Demand	45	$20 + \Delta$	30	30	125

The change was completely localized.
The change in z will be:

Change to s_i, d_j , Cell (i, j) is Basic

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	
		$10 + \Delta$	25		$35 + \Delta$
$u_2 = 3$	9	12	13	7	
	45		5		50
$u_3 = 3$	14	9	16	5	
		10		30	40
Demand	45	$20 + \Delta$	30	30	125

The change was completely localized.

The change in z will be: an increase of 6Δ

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	$35 + \Delta$
$u_2 = 3$	9	12	13	7	50
$u_3 = 3$	14	9	16	5	40
Demand	45	20	30	$30 + \Delta$	125

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	$35 + \Delta$
			10		25		Δ		
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		20		30		$30 + \Delta$		125

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	$35 + \Delta$
			10		25		Δ		
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		20		30		$30 + \Delta$		125

This creates a loop!

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	$35 + \Delta$
			10		25		Δ		
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			10				30		
Demand	45		20		30		$30 + \Delta$		125

This creates a loop! (Linear dependency)

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	
		10	25	Δ	$35 + \Delta$
$u_2 = 3$	9	12	13	7	
	45		5		50
$u_3 = 3$	14	9	16	5	
		10		30	40
Demand	45	20	30	$30 + \Delta$	125

10		Δ
10		30

$$\begin{array}{c|c} 10 & \Delta \\ \hline 10 & 30 \end{array} \rightarrow \begin{array}{c|c} 10 + \Delta & \Delta - \Delta \\ \hline 10 - \Delta & 30 + \Delta \end{array}$$

$$\begin{array}{c|c} 10 & \Delta \\ \hline 10 & 30 \end{array} \rightarrow \begin{array}{c|c} 10 + \Delta & \Delta - \Delta \\ \hline 10 - \Delta & 30 + \Delta \end{array} \rightarrow \begin{array}{c|c} 10 + \Delta & \\ \hline 10 - \Delta & 30 + \Delta \end{array}$$

$$\begin{array}{c|c} 10 & \Delta \\ \hline 10 & 30 \end{array} \rightarrow \begin{array}{c|c} 10 + \Delta & \Delta - \Delta \\ \hline 10 - \Delta & 30 + \Delta \end{array} \rightarrow \begin{array}{c|c} 10 + \Delta & \\ \hline 10 - \Delta & 30 + \Delta \end{array}$$

Corresponding to the new tableau following:

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	
		$10 + \Delta$	25		$35 + \Delta$
$u_2 = 3$	9	12	13	7	
	45		5		50
$u_3 = 3$	14	9	16	5	
		$10 - \Delta$		$30 + \Delta$	40
Demand	45	20	30	$30 + \Delta$	125

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	
		$10 + \Delta$	25		$35 + \Delta$
$u_2 = 3$	9	12	13	7	
	45		5		50
$u_3 = 3$	14	9	16	5	
		$10 - \Delta$		$30 + \Delta$	40
Demand	45	20	30	$30 + \Delta$	125

We want all these cells to remain positive...

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$		$v_2 = 6$		$v_3 = 10$		$v_4 = 2$		Supply
$u_1 = 0$		8		6		10		9	$35 + \Delta$
			$10 + \Delta$		25				
$u_2 = 3$		9		12		13		7	50
	45				5				
$u_3 = 3$		14		9		16		5	40
			$10 - \Delta$				$30 + \Delta$		
Demand	45		20		30		$30 + \Delta$		125

We want all these cells to remain positive...

Change in z :

Change to s_i, d_j , Cell (i, j) is a NBV

	$v_1 = 6$	$v_2 = 6$	$v_3 = 10$	$v_4 = 2$	Supply
$u_1 = 0$	8	6	10	9	
		$10 + \Delta$	25		$35 + \Delta$
$u_2 = 3$	9	12	13	7	
	45		5		50
$u_3 = 3$	14	9	16	5	
		$10 - \Delta$		$30 + \Delta$	40
Demand	45	20	30	$30 + \Delta$	125

We want all these cells to remain positive...

Change in z : $+6\Delta - 9\Delta + 5\Delta = +2\Delta$